

[Briggs & Stratton](#)

[Caterpillar](#)

[Coleman](#)

[Cummins](#)

[DeWalt](#)

[Guardian](#)

[Generac](#)

[Homelite](#)

[Honda](#)

[Kohler](#)

[Makita](#)

[Onan](#)

[Porter Cable](#)

[Troy-Bilt](#)

[Winco](#)

[Yamaha](#)

YAMAHA EF1000



The EF1000 is the most popular Yamaha generator - and no wonder. It's extremely quiet and offers 120V AC and 12V DC that's why it's a real hit with all types of outdoor adventurers. The EF1000 is small, easy to carry and can run a microwave, washing machine or small refrigerator. This quiet generator can run for over six hours without refueling. It delivers 1000 watts of maximum AC output with outstanding fuel efficiency. Built-in handle makes carrying a snap. Includes 12-volt DC output with protector for charging 12-volt batteries at 10-amp charge rate (charge cables included).

FEATURE	FUNCTION	BENEFIT
OHV engine (overhead valve)	- Precise valve actuation - Heavy-duty design	- Improved efficiency - Increased reliability - Quieter operation
Brushless alternator	- Reduces maintenance requirements - Clean output — high surge	- No maintenance - Years of worry-free service
Oil Watch warning system	- Automatically shuts off before oil level is low - Cannot be re-started until oil is added	- Prevents engine damage - Avoid costly repairs - Minimizes down time - Provides added peace of mind - Enhances long-term durability
Transistor Controlled Ignition (T.C.I.)	Provides clean, efficient spark	- Ensures fast, easy starting - Reliable operation - Maintenance free
Noise Suppressor	Reduces electrical interference with TVs and radios	Added convenience
Auto Decompression	Automatically "opens" valve slightly to reduce initial backpressure when starting	Effortless manual starting
USFS-approved Spark Arrestor	Keeps sparks from exiting exhaust system	- Reduces chance of fires caused by an errant spark - Quiet operation
Fuel Gauge	Monitors fuel level	Lets operator monitor how much fuel is left
AC Non-fuse Thermal Breaker	Protects AC circuit in case of an overload	- Peace of mind - Added durability
12V/10A DC Output with Charge Cord	Makes it easy to charge batteries	Added convenience
Fully enclosed design	Provides a professional appearance	Reduces noise
Tool Kit	Makes service easier	Added value

SPECIFICATIONS

TYPE	BRUSHLESS, AVR AC GENERATOR
MAXIMUM AC OUTPUT	1000 watts
RATED AC OUTPUT	850 watts
RATED / MAXIMUM AC CURRENT	7.1 / 8.3 amps @ 120V
ENGINE	OHV, FORCED AIR-COOLED, FOUR-STROKE, SINGLE CYLINDER
DISPLACEMENT / HP	84.4cc / 2.5 hp

GENERAL

OVERALL LENGTH	15.4"
OVERALL WIDTH	11.0"
OVERALL HEIGHT	15.3"
DRY WEIGHT	55.0 lbs.
FUEL TANK CAPACITY	1.0 gallons
CONTINUOUS OPERATION AT 1/2 RATED LOAD	6.3 hrs.
NOISE LEVEL	58.0 dBA
WARRANTY	2 YEARS Limited Warranty

VIEW YAMAHA MODELS

[EF1000](#)

[EF1000iS](#)

[EF2800i](#)

[EF3000iSE](#)